



Firmware Update For WJ.00.0E

Because of several new features are included into the new version and some memory allocation is changed. Before you update, please kindly check your current P2000W's firmware version. **If your P2000W's current firmware version is earlier than WJ000C**, please kindly follow the firmware update procedure in below. And this action will clear your current settings to factory default.

1. Access the web page and select the "Update S/W" page.
2. In the Update Firmware option, set "**Ignore S/W Identify Function**" to **Yes** and click the submit button.
3. In the Update System option click the Browse button  to locate the new firmware file (**WJ000e_img.ftp**). Click the Update button. Please note that the display of the Browse button depends on the language version of the Internet Explorer you are using.



The screenshot shows the ZyXEL P2000W VoIP Wi-Fi Phone web interface. The title bar is purple and reads "ZyXEL P2000W VoIP Wi-Fi Phone". The main content area has a light green background. Under the "Update Firmware" section, there is a "TFTP IP Address" field with the value "192.168.0.1" and an "Ignore S/W Identify Function" section with radio buttons for "No" and "Yes" (selected). Below these are "SUBMIT" and "CANCEL" buttons. The "Update System" section has a "Select File" field showing "C:\Documents and Settings\way\..." and an "UPDATE" button. At the bottom, there is a purple navigation bar with a "RESTART" button, a menu of links (Information, Network, OutBound Proxy, SIP Proxy, Phone Book, Wireless, DSP Setting, TOS/DS, System, Update S/W), and a "SAVE" button.

4. Once the update has been completed, the P2000W phone will automatically reboot.
5. **Reset P2000W to factory default:** Press the two buttons at the same time and power on the phone. The LCD screen will display "Load Default Factory".

